

RF6**DSP output:**

RF 6 output: 0 dB

Crossover:

Butterworth high pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

No.	Frequency	Q	Gain
1	200 Hz	4.5	-4 dB
2	275 Hz	4	-3 dB
3	608 Hz	2	-3.5db
4	5 kHz	2.5	-3 dB
5	12.4 kHz	6	-2.5 dB
6	17.2 kHz	3.5	-6 dB

High shelf filter:

No.	Frequency	Q	Gain
1	2 kHz	1	2 dB

Low shelf filter:

NA

RFS12**DSP output:**

RFS 12 output: +3dB

Crossover:

Butterworth high pass filter.

Crossover point: 30Hz

Slope: 18dB

Butterworth low pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

NA

High shelf filter:

NA

Low shelf filter:

NA

RF6**DSP output:**

RF 6 output: 0 dB

Crossover:

Butterworth high pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

No.	Frequency	Q	Gain
1	200 Hz	4.5	-4 dB
2	275 Hz	4	-3 dB
3	608 Hz	2	-3.5db
4	5 kHz	2.5	-3 dB
5	12.4 kHz	6	-2.5 dB
6	17.2 kHz	3.5	-6 dB

High shelf filter:

No.	Frequency	Q	Gain
1	2 kHz	1	2 dB

Low shelf filter:

NA

RFS12**DSP output:**

RFS 12 output: +7dB

Crossover:

Butterworth high pass filter.

Crossover point: 30Hz

Slope: 18dB

Butterworth low pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

NA

High shelf filter:

NA

Low shelf filter:

NA

RF10**DSP output:**

RF 10 output: 0 dB

Crossover:

Butterworth high pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

No.	Frequency	Q	Gain
1	144 Hz	4	-2.5 dB
2	238 Hz	4	-1.5 dB
3	520 Hz	3	-1.5db
4	4.4 kHz	3	-3 dB
5	10.6 kHz	3	-2 dB

High shelf filter:

No.	Frequency	Q	Gain
1	2 kHz	1	3.3 dB

Low shelf filter:

NA

RFS12**DSP output:**

RFS 12 output: +6dB

Crossover:

Butterworth high pass filter.

Crossover point: 30Hz

Slope: 18dB

Butterworth low pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

NA

High shelf filter:

NA

Low shelf filter:

NA

RF10**DSP output:**

RF 10 output: -3 dB

Crossover:

Butterworth high pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

No.	Frequency	Q	Gain
1	144 Hz	4	-2.5 dB
2	238 Hz	4	-1.5 dB
3	520 Hz	3	-1.5db
4	4.4 kHz	3	-3 dB
5	10.6 kHz	3	-2 dB

High shelf filter:

No.	Frequency	Q	Gain
1	2 kHz	1	3.3 dB

Low shelf filter:

NA

RFS12**DSP output:**

RFS 12 output: +7dB

Crossover:

Butterworth high pass filter.

Crossover point: 30Hz

Slope: 18dB

Butterworth low pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

NA

High shelf filter:

NA

Low shelf filter:

NA

Crossover:

Butterworth high pass filter.

Crossover point: 40Hz

Slope: 18dB

Butterworth low pass filter.

Crossover point: 19kHz

Slope: 24dB

Parametric EQ:

No.	Frequenc y	Q	Gain
1	144 Hz	3.5	-6dB
2	355 Hz	3	-4 dB
3	568 Hz	4.3	-3 dB
4	1180 Hz	3	-1.5 dB

High shelf filter:

No.	Frequenc y	Q	Gain
1	6500 kHz	0.5	7 dB

Low shelf filter:

NA

NA

RFS12**Crossover:**

Butterworth high pass filter.

Crossover point: 30Hz

Slope: 18dB

Butterworth low pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

NA

High shelf filter:

NA

Low shelf filter:

NA

Crossover:

Butterworth high pass filter.

Crossover point: 40Hz

Slope: 18dB

Butterworth low pass filter.

Crossover point: 19kHz

Slope: 24dB

DSP output:

RF 55 output: 0 dB

Parametric EQ:

No.	Frequency	Q	Gain
1	144 Hz	3.5	-6dB
2	355 Hz	3	-4 dB
3	568 Hz	4.3	-3 dB
4	1180 Hz	3	-1.5 dB

High shelf filter:

No.	Frequency	Q	Gain
1	6500 kHz	0.5	7 dB

Low shelf filter:

NA

NA

RFS12**DSP output:**

RFS 12 output: +3dB

Crossover:

Butterworth high pass filter.

Crossover point: 30Hz

Slope: 18dB

Butterworth low pass filter.

Crossover point: 80Hz

Slope: 18dB

Parametric EQ:

NA

High shelf filter:

NA

Low shelf filter:

NA