

COMMUNICATION AMPLIFIERS

iCOMC Communication Amplifiers

Two channel communication amplifiers with RS232 interface and IR remote control.

iCOMC 2X20

Mini D-class iCOMC amplifier 2x20 W with RS232 interface. 2 line and 1 microphone input, 2x20 W and 40 W bridge mode, tone control, phantom powered, LED source indication. Various input connectors to choose: RCA, Phoenix and 3.5 TRS jack. Signal source selection can be made by control button, RS232 command or IR remote control which can be purchased optionally. Mounting brackets are included into each package. Perfect device for small size installations where compact and user friendly device is necessary with possibility of remote control.



Optional accessory - IR remote control

Technical Specifications	iCOMC 2X20
Output power	2 x 20 W
Power supply	24 V DC 1,5 A
Outputs	Low impedance output - 4 Ω (screw terminal block)
Inputs	Mic: Sensitivity -60 dBu Connector - Balanced Phoenix Line 1: Sensitivity -7 dBu Connector - 3,5 mm stereo Jack Line 2: Sensitivity -7 dBu Connector - Stereo RCA
Frequency response	35 Hz - 20 kHz
THD	< 0,03 %
Signal / noise ratio	> 100 dB
Tone control	Bass ± 7 dBu , Treble ± 7 dBu
Controls	Mic and Line input level controls, balance control, tone control, input selector, loudness, limiter and phantom power. RS 232 and IR remote controls.
Indicators	Power, volume, balance, tone
Dimensions	145 mm x 120 mm x 45 mm
Weight	0,6 kg
Colour	Black (RAL 9017)